

FD-600 Folded Dipole HF Antenna

Commercial Series, 2-30Mhz Broadband Design

DR DIGITAL HF VOICE & DATA
RADIO COMPATIBLE

Product Information

The Bushcomm FD-600 is a **High Power** compact, two wire folded dipole alternative to our best-selling model, the BBA-100 three wire broad-band antenna.


The FD-600 Folded Dipole covers the frequency range of 2-30Mhz, and has a rated power input of **600W PEP**. Best of all, as with the majority of our antennas, **no tuner is required**.

The Folded Dipole is a multi-wire that is relatively light in weight. By having only two stainless steel wires compared to the BBA-100's three wires, it also has less wind loading and an SWR of better than 2.5 (typically 1.5-1.6).




Built to withstand the rigours of the world's harshest environments.

RECOMMENDED INSTALLATION CONFIGURATIONS



ABOVE: HORIZONTAL CONFIGURATION



ABOVE: INVERTED "V" CONFIGURATION

SPECIAL FEATURES

- NO TUNER REQUIRED
- UV RESISTANT SPACER RODS
- UV RESISTANT BALUN/LOAD BOXES
- STAINLESS STEEL WIRE & FITTINGS

Specifications:

ELECTRICAL

Frequency Range: 2-30MHz
Input Impedance: 50 Ohms
Power Input: 600W PEP (voice) / 250W Continuous Data Modes
Input Connector: UHF-type socket

MECHANICAL

Shipping Weight: 5kg
Antenna Length: 27m
Mast Spacing: 29m Horizontal configuration
18m inverted "v" configuration (with a 10m tower)

Contact:

Bushcomm Antennas
21 River Road, Bayswater, WA, 6053
Australia
EMAIL: sales@bushcommantennas.com
WEBSITE: www.bushcomm.com
PHONE: + 61 8 6144 3204
FAX: +61 8 9378 4429

FOR FURTHER INFORMATION
VISIT OUR WEBSITE
www.bushcomm.com